



Construction

The GEMÜ 1210 proximity sensor housing is made of stainless steel and has two mounting threads for proximity switches. The housing is fixed to the mounting kit by grubscrews and sealed by O-rings.

Features


- For linear actuators upto 40 mm stroke
- · Stainless steel housing
- · Optical position indicator optional
- Available for M8x1 or M12x1 proximity switches
- Compact design

Advantages

 Damping surface of proximity switches protected against damage and cleaning agents



Sectional drawing






FEMU® 1210



Technical data

Dimensions - GEMÜ 1210 [mm]



Stroke (Code)	A	A 1	A2	ØВ	Н	М	
06	57.5	39	23	29.5	-	M8x1	
00	57.5					M12x1	
10	66.0	43	23	39.5	6	M8x1	
10						M12x1	
20	78.0	55	22	39.5	23 39.5		M8x1
20			23		6	M12x1	
40	98 75	23	48	6	M8x1		
		75	23	40	0	M12x1	

Order data

Version	Code
	000

Stroke	Code
For upto 6 mm stroke	06
For upto 10 mm stroke	10
For upto 20 mm stroke	20
For upto 40 mm stroke	40

Optical indication	Code
With optical indication	Υ
Without optical indication	N

Proximity switch size	Code
For M8 x 1 proximity switches	08
For M12 x 1 proximity switches	12

Order example	1210	000	Z	20	Υ	08
Туре	1210					
Version (code)		000				
Accessory (code)			Z			
Stroke (code)				20		
Optical indication (code)					Υ	
Proximity switch size (code)						08

Note: Mounting kit 1210S01Z... depends on the valve type. Please order separately specifying valve type, DN, control function and actuator size. The stroke (code) of the mounting kit determines the stroke (code) of the proximity sensor housing.



